

## Mini Car Inverter 150W with USB – CAR151



### Products Description :

JYINS mini car inverter convert 12/24V DC into 100-120V/220-240V AC, Only simply plug your inverter into the cigarette lighter socket from the console in your vehicle then get power for your electronic devices such as laptops, DC players, phone chargers etc. USB charging port offers an additional choice for user. It can charge for digital equipments.

### Products Features :

- Small in size , light in weight and potable
- Easy to use and high efficiency
- Green LED for indicates the power on
- Input & output isolation
- Muti-protection function
- USB output port: 5V500mA
- A,B,C,C,D,E,F,G socket optional

### Protection Features:

- Low voltage protection

# JYINS<sup>®</sup>

Shang hai JINGYING METRE ELECTRIC CO.,LTD.

ADDRESS: Huancheng East Road, Jingying Industrial Zone, Liushi Yueqing City,  
Zhejiang Province, China  
POSTCODE: 325604  
FAX:86-577-62775560 62792655  
TEL: 400-021-5560  
http://www.jyins.com E-mail: jyins@jyins.com

- Over voltage protection
- Overload protection
- Over temperature protection
- Short circuit protection

**Details :**

Model	CAR151-121	CAR151-122	CAR151-241	CAR151-242
Rated power	150W			
Surge power	300W			
Output voltage	110V	230V	110V	230V
Output frequency	50/60Hz ±3			
USB port	5V 500mA			
Output waveform	Modified Sine Wave			
Input voltage	12V		24V	
Dimension	145*76*54mm (L*W*H)			
N.W/unit	365g			
QTY/Ctn	40pcs			
Packing	Gift box			
Meas./Ctn	51*37*42.5cm			
Brand	JYINS or OEM			
Certification	CE-EMC/LVD,RoHS, E-mark			
Warranty	18 months			