

Mini Car Inverter 200W with USB – CAR2000U



Products Description :

JYINS mini car inverter convert 12/24V DC into 100-120V/220-240V AC, Only simply plug your inverter into the cigarette lighter socket from the console in your vehicle then get power for your electronic devices such as laptops, DC players, phone chargers etc. USB charging port offers an additional choice for user. It can charge for digital equipments.

Products Features :

- Small in size , light in weight and potable
- Easy to use and high efficiency
- Green LED for indicates the power on
- Input & output isolation
- Muti-protection function
- USB output port: 5V500mA

Protection Features:

- Low voltage protection
- Over voltage protection

JYINS[®]

Shang hai JINGYING METRE ELECTRIC CO.,LTD.

ADDRESS: Huancheng East Road, Jingying Industrial Zone, Liushi Yueqing City,
Zhejiang Province, China
POSTCODE: 325604
FAX:86-577-62775560 62792655
TEL: 400-021-5560
http://www.jyins.com E-mail: jyins@jyins.com

- Overload protection
- Over temperature protection
- Short circuit protection

Details :

Model	CAR2000U-121	CAR2000U-122	CAR2000U-241	CAR2000U-242
Rated power	200W			
Surge power	400W			
Output voltage	110V	230V	110V	230V
Output frequency	50/60Hz ±3			
USB port	5V 500mA (optional)			
Output waveform	Modified Sine Wave			
Input voltage	12V		24V	
Dimension	87*73*43mm (L*W*H)			
N.W/unit	255g			
QTY/Ctn	40pcs			
Packing	Gift box			
Meas./Ctn	58*30*38.5cm			
Brand	JYINS or OEM			
Certification	CE-EMC/LVD,RoHS, E-mark			
Warranty	18 months			

Note : if without USB, the model is CAR2000

JYINS[®]

Shang hai JINGYING METRE ELECTRIC CO.,LTD.

ADDRESS: Huancheng East Road, Jingying Industrial Zone, Liushi Yueqing City,
Zhejiang Province, China
POSTCODE: 325604
FAX:86-577-62775560 62792655
TEL: 400-021-5560
http://www.jyins.com E-mail: jyins@jyins.com