

## Smart Digital Car Inverter- CAR120D



### Products Description :

JYINS smart car inverter convert 12/24V DC into 100-120V/220-240V AC, Only simply plug your inverter into the cigarette lighter socket from the console in your vehicle then get power for your electronic devices such as laptops, DC players, phone chargers etc. USB charging port offers an additional choice for user. It can charge for digital equipments.

### Products Features :

- Digital display : Volt, Watts, and Protection status
- Smart and potable
- Easy to use and high efficiency
- Input & output isolation
- Muti-protection function
- USB output port: 5V500mA
- Output socket: A,B,C,D,E,F,G optional

### Protection Features:

- Low voltage protection

# JYINS<sup>®</sup>

Shang hai JINGYING METRE ELECTRIC CO.,LTD.

ADDRESS: Huancheng East Road, Jingying Industrial Zone, Liushi Yueqing City,  
Zhejiang Province, China  
POSTCODE: 325604  
FAX:86-577-62775560 62792655  
TEL: 400-021-5560  
http://www.jyins.com  
E-mail: jyins@jyins.com

- Over voltage protection
- Overload protection
- Over temperature protection
- Short circuit protection

**Details :**

Model	CAR120D-121	CAR120D-122	CAR120D-241	CAR120D-242
Rated power	120W			
Surge power	240W			
Output voltage	110V	230V	110V	230V
Output frequency	50/60Hz ±3			
USB port	5V 500mA (optional)			
Output waveform	Modified Sine Wave			
Input voltage	12V		24V	
Dimension	108*66*45mm (L*W*H)			
LED & digital display	Volt, Watts, Protection Status			
N.W/unit	265g			
QTY/Ctn	40pcs			
Packing	Double-side Blister			
Meas./Ctn	48*32*46cm			
Brand	JYINS or OEM			
Certification	CE-EMC/LVD,RoHS, E-mark			
Warranty	18 months			